

## Consumo de Corriente en Motores

HP's	Amperaje 220 VCA	Amperaje 440 VCA
.5 hp	2	1
.75 hp	2.8	1.4
1 hp	3.6	1.8
1.5 hp	5.2	2.6
2 hp	6.8	3.4
3 hp	9.6	4.8
5 hp	15.2	7.6
7.5 hp	22	11
10 hp	28	14
15 hp	42	21
20 hp	54	27
25 hp	68	34
30 hp	80	40
40 hp	104	52
50 hp	130	65
60 hp	154	77
75 hp	192	96
100 hp	248	124
125 hp	312	156
150 hp	360	180
200 hp	480	240